




Schedule 80 Fittings

30° EII


Socket x Socket



Part Number	Size	H	J	M	Approx. Wt. (Lbs.)
815-005F	1/2	1- 7/16	7/16	1- 1/8	.08
815-007F	3/4	1- 7/16	7/16	1- 3/8	.11
815-010F	1	1- 3/4	1/2	1-11/16	.13
815-012F	1-1/4	2- 3/16	11/16	2- 1/16	.27
815-015F	1-1/2	2- 3/16	11/16	2- 5/16	.33
815-020F	2	2- 1/2	3/4	2-13/16	.54
815-025F	2-1/2	3	1	3- 7/16	.81
815-030F	3	3- 5/16	1- 1/16	4- 1/8	1.34
815-040F	4	3- 7/16	1- 3/16	5- 3/16	2.08
815-045F	4-1/2	4	1- 1/2	5- 5/8	2.78
815-050F	5	4- 3/8	1- 3/8	6- 5/16	3.09
815-060	6	4-13/16	1- 7/8	7- 9/16	5.59
815-080F	8	6- 3/16	1-15/16	9- 5/8	7.57
815-100F	10	7- 3/4	2- 1/2	11-15/16	16.93
815-120F	12	9- 1/16	2-13/16	14- 1/8	27.92
815-140F	14	10- 7/16	3- 7/16	15- 1/2	37.94
815-160F	16	11-15/16	3-15/16	17-11/16	55.09
815-180F	18	13- 7/16	4- 7/16	19- 7/8	77.09
815-200F	20	15	5	22- 1/16	119.89
815-240F	24	18- 1/8	6- 1/8	26- 7/16	15.46

22-1/2° EII

Socket x Socket



Part Number	Size	H	J	M	Approx. Wt. (Lbs.)
816-005	1/2	1- 1/16	3/16	1- 5/32	.05
816-007	3/4	1- 3/16	3/16	1- 7/16	.08
816-010	1	1- 3/8	9/32	1-23/32	.13
816-010F	1	1-3/4	1/2	1-11/16	.15
816-015F	1-1/2	2- 1/8	5/8	2- 5/16	.28
816-012	1-1/4	1- 1/2	5/16	2- 3/32	.19
816-015	1-1/2	1-21/32	1/4	2- 3/8	.25
816-020	2	1- 7/8	7/16	2- 7/8	.38
816-025	2-1/2	2- 7/32	15/32	3- 1/2	.68
816-025F	2-1/2	2- 7/8	7/8	3- 7/16	.83
816-030	3	2-13/32	9/16	4- 5/32	.96