


**Schedule 80 Fittings**



**22-1/2° EII**

Socket x Socket


(Continued)



Part Number	Size	H	J	M	Approx. Wt. (Lbs.)
816-040	4	2- 7/8	5/8	5- 1/4	1.64
816-045F	4-1/2	3-13/16	1- 5/16	5- 5/8	2.55
816-050F	5	4- 1/8	1- 1/8	6- 5/16	2.97
816-060	6	4- 9/16	1- 3/8	7- 7/16	4.33
816-060F	6	4- 5/8	1- 3/8	7- 1/2	4.87
816-080	8	5- 1/16	1- 1/32	9- 3/4	8.18
816-080F	8	5- 7/8	1- 5/8	9- 5/8	7.06
816-100F	10	7- 5/16	2- 1/16	11-15/16	15.94
816-120F	12	8- 9/16	2- 5/16	14- 1/8	26.53
816-140F	14	9-13/16	2-13/16	15- 1/2	36.29
816-160F	16	11- 5/16	3- 5/16	17-11/16	52.97
816-180F	18	12- 3/4	3- 3/4	19- 7/8	74.44
816-200F	20	14- 1/4	4- 1/4	22- 1/16	119.89
816-240F	24	17- 3/16	5- 3/16	26- 7/16	189.95

**45° EII**

Socket x Socket



Part Number	Size	H	J	M	Approx. Wt. (Lbs.)
817-002	1/4	13/16	5/32	27/32	.02
817-003	3/8	31/32	7/32	1	.03
817-005	1/2	1- 1/8	1/4	1- 3/16	.06
817-007	3/4	1- 5/16	5/16	1- 7/16	.09
817-010	1	1- 7/16	5/16	1-23/32	.14
817-012	1-1/4	1- 5/8	3/8	2- 1/8	.21
817-015	1-1/2	1-13/16	7/16	2- 3/8	.30
817-020	2	2- 1/8	5/8	2- 7/8	.45
817-025	2-1/2	2-13/32	21/32	3- 1/2	.85
817-030	3	2-29/32	29/32	4- 5/32	1.16
817-040	4	3- 5/16	1- 1/16	5- 1/4	1.98
817-045F	4-1/2	4- 1/2	2	5- 5/8	2.62
817-050	5	4	1-11/32	6-13/32	3.28
817-050F	5	4- 7/8	1- 7/8	6- 5/16	3.34
817-060	6	4- 3/4	1- 3/4	7-19/32	5.46
817-080	8	6	2	9- 3/4	10.16
817-100	10	7-5/8	2-19/32	12-1/8	18.98




**Schedule 80 Fittings**

**45° EII**

Socket x Socket


(Continued)



Part Number	Size	H	J	M	Approx. Wt. (Lbs.)
817-100F	10	8-11/16	3- 7/16	11-15/16	17.37
817-120	12	9-3/16	3-1/8	14-3/8	31.85
817-120F	12	10- 1/8	3- 7/8	14- 1/8	30.72
817-140	14	10- 5/16	3- 5/16	15- 5/8	39.65
817-140F	14	11- 9/16	4- 9/16	15- 1/2	41.24
817-160F	16	13- 5/16	5- 5/16	17-11/16	61.44
817-180F	18	15	6	19- 7/8	87.73
817-200F	20	16- 3/4	6- 3/4	22- 1/16	112.97
817-240F	24	20- 3/16	8- 3/16	26- 7/16	204.20

**15° EII**

Socket x Socket



Part Number	Size	H	J	M	Approx. Wt. (Lbs.)
818-020F	2	2- 5/16	9/16	2-13/16	.38
818-025F	2-1/2	2- 3/4	3/4	3- 7/16	.79
818-030F	3	3	3/4	4- 1/8	1.17
818-040F	4	3- 1/8	7/8	5- 3/16	1.62
818-045F	4-1/2	3- 5/8	1- 1/2	5- 5/8	2.31
818-050F	5	3-15/16	15/16	6- 5/16	2.98
818-060F	6	4- 3/8	1- 1/8	7- 1/2	4.42
818-080F	8	4- 1/2	1- 1/4	9- 5/8	6.56
818-100F	10	6-15/16	1-11/16	11-15/16	14.94
818-120F	12	8- 1/16	1-13/16	14- 1/8	25.13
818-140F	14	9- 5/16	2- 5/16	15- 1/2	34.64
818-160F	16	10-11/16	2-11/16	17-11/16	50.85
818-180F	18	12- 1/16	3- 1/16	19- 7/8	71.78
818-200F	20	13- 1/2	3- 1/2	22- 1/16	119.89
818-240F	24	16- 1/4	4- 1/4	26- 7/16	170.96