




Schedule 80 Fittings

Grooved Coupling Adapter

(Continued)


Groove x Socket



| Part Number | Size | L | M1 | N | Approx. Wt. (Lbs.) |
|-------------|------|---------|----------|---------|--------------------|
| 833-040 | 4 | 4-17/32 | 5- 1/4 | 2- 9/32 | 1.27 |
| 833-050F | 5 | 7 | 6- 5/16 | 4 | 2.48 |
| 833-060 | 6 | 5- 5/16 | 7- 9/16 | 2- 5/16 | 2.78 |
| 833-080F | 8 | 8- 3/16 | 9- 5/8 | 3-15/16 | 5.70 |
| 833-100F | 10 | 9- 7/8 | 11-15/16 | 4- 5/8 | 10.35 |
| 833-120F | 12 | 10- 7/8 | 14- 1/8 | 4- 5/8 | 16.21 |

Female Adapter

Socket x Fipt



| Part Number | Size | L | M | N | Approx. Wt. (Lbs.) |
|-------------|---------|---------|----------|---------|--------------------|
| 835-002 | 1/4 | 1-11/32 | 27/32 | 3/32 | .02 |
| 835-003 | 3/8 | 1-15/32 | 1 | 3/32 | .03 |
| 835-098 | 3/4X1/4 | 1-15/16 | 1-13/32 | 13/32 | .05 |
| 835-005 | 1/2 | 1-23/32 | 1- 5/32 | 3/32 | .04 |
| 835-007 | 3/4 | 1-27/32 | 1-13/32 | 3/32 | .06 |
| 835-010 | 1 | 2- 1/8 | 1-23/32 | 3/32 | .11 |
| 835-012 | 1-1/4 | 2- 5/16 | 2- 3/32 | 3/32 | .17 |
| 835-015 | 1-1/2 | 2- 1/2 | 2-11/32 | 3/32 | .20 |
| 835-020 | 2 | 2-11/16 | 3 | 1/4 | .40 |
| 835-025 | 2-1/2 | 3- 1/4 | 3- 9/16 | 7/32 | .63 |
| 835-030 | 3 | 3-15/32 | 4- 1/4 | 3/16 | .74 |
| 835-040 | 4 | 3-31/32 | 5- 7/32 | 1/4 | 1.21 |
| 835-060 | 6 | 4-31/32 | 7-21/32 | 5/16 | 3.08 |
| 835-080 | 8 | 6- 5/32 | 9-23/32 | 1/4 | 5.22 |
| 835-080F | 8 | 8- 9/16 | 9- 5/8 | 2- 9/16 | 6.18 |
| 835-100F | 10 | 10- 1/4 | 11-15/16 | 3 | 10.50 |
| 835-120F | 12 | 11- 1/8 | 14- 1/8 | 2- 5/8 | 14.09 |