




Schedule 80 Fittings


Cap
Socket

(Continued)



Part Number	Size	M	W	Approx. Wt. (Lbs.)
847-030	3	4- 5/32	3- 1/32	.70
847-040	4	5- 1/4	3-19/32	1.16
847-050F	5	6- 1/2	4- 7/16	1.85
847-060	6	7- 1/2	4- 7/8	3.11
847-080	8	9-23/32	6- 3/8	6.30
847-100F	10	12- 1/4	5-15/16	7.89
847-120F	12	14- 1/4	7- 1/8	11.29
847-140F	14	15- 1/2	7- 3/8	13.19
847-160F	16	17- 7/8	9	24.27
847-180F	18	19-15/16	9- 1/4	32.09
847-200F	20	22	14-1/4	49.04
847-240F	24	26- 3/8	17- 1/4	89.38

Cap
Fipt



Part Number	Size	M	W	Approx. Wt. (Lbs.)
848-002	1/4	29/32	15/16	.01
848-003	3/8	31/32	29/32	.01
848-005	1/2	1- 3/16	1- 1/16	.03
848-007	3/4	1- 3/8	1- 7/32	.04
848-010	1	1-27/32	1- 7/16	.10
848-012	1-1/4	2- 7/32	1-17/32	.14
848-015	1-1/2	2-17/32	1- 5/8	.19
848-020	2	3- 5/32	1-25/32	.28
848-025	2-1/2	3- 5/8	2- 7/16	.53
848-030	3	4- 3/8	2- 7/16	.75
848-040	4	5- 7/16	3- 1/16	1.32
848-060F	6	7- 3/16	4- 3/8	2.07
848-080F	8	9- 3/8	4- 3/8	3.52
848-100F	10	11-7/8	5-3/4	7.42
848-120F	12	13-13/16	6-3/16	10.77